

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

**(19) World Intellectual Property Organization
International Bureau**



(43) International Publication Date
18 December 2003 (18.12.2003)

(10) International Publication Number
WO 03/105384 A1

**(51) International Patent Classification⁷: H04J 14/02,
H04B 10/18**

(21) International Application Number: PCT/GB03/02508

(22) International Filing Date: 11 June 2003 (11.06.2003)

(25) Filing Language: English

(26) **Publication Language:** English

(30) Priority Data:
0213385.8 11 June 2002 (11.06.2002) GB

(71) Applicant (for all designated States except US): MAR-
CONI UK INTELLECTUAL PROPERTY LTD
[GB/GB]; New Century Park, P.O. Box 53, Coventry CV3
1HJ (GB).

(72) Inventor; and

(75) **Inventor/Applicant (for US only): CLARINGBURN, Harry, Richard** [GB/GB]; 49 Fernleigh Avenue, westdale Lane, Nottingham NG3 6FN (GB).

(74) **Agent: WATERS, Jeffrey;** Marconi Intellectual Property, Marrable House, Vineyards, Great Baddow, Chelmsford, Essex CM2 7QS (GB).

(81) Designated States (national): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, OM, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.

(84) Designated States (regional): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GO, GW, ML, MR, NE, SN, TD, TG).


Published:

— with international search report

— before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: MAXIMISING POWER IN OPTICAL COMMUNICATION NETWORKS



(57) Abstract: The relative launch power of signals at an add/drop node transponder is controlled to maximise available power. Known values of signal bandwidth and likely noise in the signal path (8), for example, derived from the system manager (24.9), are used to control (22) the launch power (23) into the optical amplifier (11), in order to optimise the launch power accordingly.

BEST AVAILABLE COPY

3/05/03
1

MAXIMISING POWER IN OPTICAL COMMUNICATIONS NETWORKS

This invention relates to optical communications networks, and in particular to maximising power available to launch signals onto optical communications networks.

The design of photonics systems requires that the OSNR (optical signal to noise ratio) is above a given minimum value over the longest path under the worst case
5 conditions.

Optical communication systems, such as wavelength division multiplex (WDM) systems typically use optical amplifiers in the signal path. A limiting feature of optical amplifiers is the power available. This may be due to safety constraints or cost. The maximum output power of an amplifier is conventionally divided equally amongst all
10 the channels being transmitted.

However, higher bit rate channels such as 10Gbit/s require a better OSNR than lower bit rate channels such as 2.5Gbit/s channels. It has been proposed (EP-A-0 924 888) to adjust the optical power in individual channels by measuring optical power along the transmission path in use. However, the processing overload for this is
15 relatively high.

Also, it has been proposed (WO 02/09299) to compensate for wavelength dependent gain and noise profiles by pre-emphasising individual channels of a WDM by values obtained by measuring the OSNR of the undistorted channels.

The invention aims to maximise the power available to signals requiring a higher
20 bandwidth and or greater path length. Broadly, this is achieved by dividing available output power amongst the channels according to their individual bandwidth/distance requirements.

More specifically, there is provided a method of controlling signal launch power in an optical communications network, comprising pre-distorting the launch power in accordance with known values of at least one of bandwidth and expected noise on the signal path.

5 The invention also provides apparatus for controlling signal launch power in an optical communications network, comprising a launcher for launching a signal onto the network, and means for pre-distorting the launch power in accordance with known values of at least one of bandwidth and expected noise on the signal path.

10 This has the advantage that launch power can be conserved and redirected to maximise the bandwidths that can be transmitted and to increase the path lengths over which signals can be transmitted, without incurring a processing overload due to making measurements.

Preferably, the optical communications network carries an n channel signal multiplex, and a plurality of signals are launched from a network node.

15 Preferred embodiments have the advantage that for a given launch power available at an add/drop node, the power can be distributed amongst the channels in accordance with the requirements of each channel. This again can increase the bandwidth that can be sent and increase the transmission distance that can be achieved.

20 The noise is generated at the optical amplifiers, and the expected noise can be determined knowing the route of the signal, that is, the number and type of optical amplifiers the signal will pass through in the network. This will be indicative of the OSNR. The known values may be provided by management systems of the optical communication systems, for example, by the network manager, or by a shelf manager. Equally, the known values may be provided by data passed along a supervisory channel.

In a preferred embodiment, the pre-distorted signals are passed through an optical amplifier, and the launch power is pre-distorted using a comparator. A separate comparator is provided for each channel of the optical multiplex, a suitable demultiplexer being provided at the output of the optical amplifier. One input to the
5 comparator is a signal, preferably electrical, derived from the output of the optical amplifier for any particular channel, while the other is representative of the known values of at least one of bandwidth and expected noise on the signal path through the network for that channel. The output of the comparator controls the launch power of the signal for that channel into the optical amplifier, for example, by means of a variable
10 optical attenuator for a through channel, or a transponder for an added channel.

An embodiment of the invention will now be described, by way of example only, and with reference to the accompanying drawings, in which:

Figure 1 is a schematic diagram illustrating the principle of the invention;

Figure 2 is a schematic diagram showing how launch power can be adjusted
15 according to the connection path; and

Figure 3 shows the invention applied to an optical ring network.

The embodiments described divide the available output power amongst the channels according to individual bandwidth requirements. The higher the bit rate, the higher the power level allocated to that channel ensuring that all channels are launched
20 such that they are received with adequate OSNR.

The power output for a given channel can also be controlled according to the number and type of network elements the signal is to pass through.

Referring to Figure 1, an optical amplifier 10 amplifies a WDM optical signal on a fibre 11. The output is split at a coupler 12 providing an output signal path 13 and a

feedback control path 15. The feedback control path is demultiplexed by a demultiplexer 14 the outputs of which each have a pin diode 16 attached to convert the individual channels signals into electrical signals. Only one is shown in Figure 1 for simplicity. The electrical signals are amplified by amplifier 18 and then passed to a
5 controller 22 the outputs of which are connected to transponder 20 or CCU 23 (a variable optical attenuator array) depending on whether a channel is being added or passed through. In practice, the amplifier will amplify a number of channels, for example up to 32, but there is a separate controller 22 for each channel. Each controller acts as a comparator, which compares the output of the amplifier 18, indicative of the
10 power amplitude of the channel at the output of the optical amplifier, with a reference level, chosen so that the output of the comparator, which is fed to the CCU or the transponder, produces a launch signal of the desired power for that channel as input to the optical amplifier.

In accordance with the invention, the launch power of each channel is pre-
15 distorted in accordance with the known bandwidth of each channel (its bit rate) and in accordance with the noise expected to be added to each signal in consequence of its routing.

The controller 22 receives the network and connectivity information 8 required to assess the bandwidth and the routing from a shelf management unit 24 under the
20 overall control of network manager 9 and, knowing the power of the channel, its bandwidth and the OSNR of the path, alters the reference at the comparator input to control the launched power of the channel to optimise it. Thus, for example, it can be ensured that the signal is not launched with too much power as this would waste a power resource that could be directed to a higher bit rate channel.

Each channel may carry a different signal having a different bandwidth and therefore have a different launch power requirement. The system manager can evaluate each signal's power requirement for its known bandwidth and routing. The system manager can then formulate a target power level for the controller to set the launched power level. Thus, the available launch power is not simply divided equally across the channels but distributed according to a measure of channel power requirement, such as signal bandwidth and noise expected to be added, both as regards the number of optical amplification stages passed through and as regards the type of optical amplifier passed through.

Although the launch power is adjusted to take account of bit rate and signal routing, it would be possible for the launch power to take account of one of these only.

Turning now to Figure 2, the circuit illustrated schematically shows how the connection path can be determined. The figure illustrates a portion of an add/drop node which adds signals on to the network.

Thus, the add side of the add/drop node comprises a channel control unit 30 to control through traffic and an add coupler 32 for addition of signals to the network. The signals to be added are provided from the transmitters of node transponders 34 which output a number of signals on separate channels, for example up to 32. These signals are multiplexed together by an optical multiplexer 36 and the signal multiplex added onto the network by the coupler 32.

The output of the coupler is amplified by an optical amplifier 38 and a signal split from the main network path to derive a feedback signal by a splitter coupler 40. The coupler 40 has two outputs: a through output 42 which is the main network path, and a drop path 44 from which the feedback signal is derived. The drop path 44 carries

the dropped signal multiplex to a demultiplexer 46 where it is split into its component channels. A feedback signal is derived for each of the these channels, one only of which is shown in Figure 2. The optical output of the channel from demultiplexer 46 is converted to an electrical signal by photodiode 48, amplified by amplifier 50 and fed
5 back to the controller block 22 where the feedback signal is compared with a reference signal and a control output generated to adjust the transponder. The reference signal is derived from the signal bandwidth and routing information stored in blocks similar to blocks 8, 24 and 9 of Figure 1, but not shown in Figure 2, and used in the controller 22 as before.

10 The signal on the through path continues around the network until it reaches its destination, whereupon the signal is dropped to a receiver. Where a channel passes through a node the levelling controller block will control the amplitude of the channel for the current received relative amplitude. The signal will pass through various stages of processing depending on how long it stays on the network. Each of these will
15 introduce an amount of noise onto the signal. In the example of Figure 2, the signal is shown as passing through three amplification stages 52, 54, 56 by way of example. Each of these adds an element of noise N to the signal. Thus, the total signal noise will depend on the route taken by the signal to its destination.

This signal is eventually dropped to the receiving node by a split coupler 58,
20 filtered by a band pass filter 60 to isolate the signal channel and passed to a receiver Rx 62 where it is converted to an electrical signal for the user. The controller block 22 knows the noise on the signal at the receiver, and the bandwidth of the signal, from the blocks similar to blocks 8, 24 and 9 in Figure 1, and can adjust the launch power of the signal accordingly.

The transponder seeks to send the signal with just sufficient power to exceed the minimum OSNR thereby optimising power utilisation. As with the previous example of Figure 1, the controller 22 seeks to distribute the launch power to optimise the power for the bandwidth and paths of the signals.

5 Figure 3 shows schematically how the network manager is attached to a ring network 60, via gateway nodes 70, to manage the flow of traffic between these nodes and other nodes 71. The various amplifiers between the nodes, such as amplifiers 52, 54 and 56 operate at a constant gain. It is therefore possible for the network manager to determine the noise contribution of each amplifier and to determined the signal path.
10 Thus, the network manager can provide the add/drop node transponder launching the signal with an indication of the likely noise on the signal. The network manager will always be aware of the signal path, including, for example, cases where a signal is sent round the longer of the two paths on a two fibre ring network, due to a component failure or the like on the shorter path.

15 It will be appreciated from the above description that embodiments of the invention have the advantage of allowing the launch power for a signal to be chosen according to parameters of the signal such as bandwidth and signal path. This enables available launch power to be distributed intelligently according to channel requirements. Moreover, it can enable other channels to be used at higher bandwidths or greater
20 distances than would otherwise be possible.

Various modifications to the embodiments described are possible and will occur to those skilled in the art without departing from the scope of the invention. For example, instead of using the network and shelf manager to provide the expected routing to the block 8, this information could be provided by the supervisory channel, which

could record the number and types of optical amplifiers which channels have passed through. In the case of Figure 3, a knowledge of the type of amplifier to be passed through by a signal propagating from gateway node 70 to node 71, could be extracted from a signal which has passed through the node 71 in the reverse direction on its way
5 to the node 70, since the optical amplifiers for each direction in a node will often be identical.

CLAIMS

1. A method of controlling signal launch power in an optical communications network, comprising pre-distorting the launch power in accordance with known values of at least one of bandwidth and expected noise on the signal path.
2. A method as claimed in claim 1, wherein the known values are provided by management systems of the optical communication network.
3. A method as claimed in claim 2, wherein the known values are provided by a network and connectivity information unit.
4. A method as claimed in claim 2, wherein the known values are supplied by a supervisory channel.
5. A method as claimed in any one of claims 1 to 4, wherein the pre-distorted signals are passed through an optical amplifier.
6. A method as claimed in claim 5, wherein the signal launch power is pre-distorted using a comparator, which compares a signal derived from the output of the optical amplifier with a reference signal dependent on the known values of at least one of bandwidth and expected noise.
7. A method as claimed in any one of claims 1 to 6, in which the expected noise on the signal path is derived from a knowledge of the number and type of optical amplifiers the signal will pass through in the optical communications network.
8. A method as claimed in any one of claims 1 to 7, in which the optical communications network carries an n channel multiplex, the launch powers of all of which through an optical amplifier are pre-distorted.

9. A method as claimed in any one of claims 1 to 8, in which the launch power is pre-distorted to increase the signal level of signals having a higher bandwidth compared to those having a lower bandwidth.
10. A method as claimed in any one of claims 1 to 9, in which the launch power is pre-distorted to increase the signal level of signals having a higher expected noise through the network compared to those having a lower expected noise.
11. Apparatus for controlling signal launch power in an optical communications network, comprising a launcher for launching a signal onto the network, and means for pre-distorting the launch power in accordance with known values of at least one of bandwidth and expected noise on the signal path.
12. Apparatus as claimed in claim 11, wherein the known values are provided in use by management systems of the optical communication network.
13. Apparatus as claimed in claim 12, wherein the known values are provided by a network and connectivity information unit.
14. Apparatus as claimed in claim 12, wherein the known values are supplied by a supervisory channel.
15. Apparatus as claimed in any one of claims 11 to 14, including an optical amplifier through which the pre-distorted signals are passed in use.
16. Apparatus as claimed in claim 15, wherein the pre-distorting means includes a comparator, arranged to compare a signal derived from the output of the optical amplifier with a reference signal dependent on the known values of at least one of bandwidth and expected noise.

17. Apparatus as claimed in any one of claims 11 to 16, in which the number and type of optical amplifiers the signal will pass through in the optical communications network is used to derive the expected noise on the signal path.
 18. Apparatus as claimed in any one of claims 11 to 17, in which the optical communications network is adapted to carry an n channel multiplex, the launch powers of all of which through an optical amplifier are pre-distorted in use.
 19. Apparatus as claimed in any one of claims 11 to 18, in which the pre-distorting means is arranged to increase the signal level of signals having a higher bandwidth compared to those having a lower bandwidth.
 20. Apparatus as claimed in any one of claims 11 to 19, in which the pre-distorting means is arranged to increase the signal level of signals having a higher expected noise through the network compared to those having a lower expected noise.
 21. Apparatus as claimed in any one of claims 11 to 20, in which the apparatus is an add/drop node.
- }




Figure 1





Figure 2

**Figure 3**

INTERNATIONAL SEARCH REPORT

International Application No.

PCT/GB 03/02508

A. CLASSIFICATION OF SUBJECT MATTER
 IPC 7 H04J14/02 H04B10/18

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04J H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	EP 0 924 888 A (NORTHERN TELECOM LTD) 23 June 1999 (1999-06-23) cited in the application abstract paragraphs '0006!-'0011! paragraphs '0017!', '0021! figure 1	1-21
X	WO 02 09299 A (SYCAMORE NETWORKS INC) 31 January 2002 (2002-01-31) cited in the application abstract page 4, line 19 -page 7, line 2 figures 1,3	1-21

-/--

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents:

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

T later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

X document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

Y document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

G document member of the same patent family

Date of the actual completion of the international search

10 October 2003

Date of mailing of the international search report

23/10/2003

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
 NL - 2280 HV Rijswijk
 Tel (+31-70) 340-2040, Tx. 31 651 epo nl,
 Fax (+31-70) 340-3016

Authorized officer

Helms, J

INTERNATIONAL SEARCH REPORT

International Application No.

PCT/GB 03/02508

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	EP 0 543 570 A (AMERICAN TELEPHONE & TELEGRAPH) 26 May 1993 (1993-05-26) abstract page 3, line 45 -page 5, line 41 figures 1,2,7 -----	1-21
X	DE 198 48 989 A (SIEMENS AG) 11 May 2000 (2000-05-11) page 2, line 56 -page 4, line 25 figure 1 -----	1-21

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/GB 03/02508

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
EP 0924888	A	23-06-1999	US 6040933 A	21-03-2000
			EP 0924888 A2	23-06-1999
WO 0209299	A	31-01-2002	AU 7892501 A	05-02-2002
			WO 0209299 A2	31-01-2002
			US 2002015201 A1	07-02-2002
EP 0543570	A	26-05-1993	US 5225922 A	06-07-1993
			CA 2078482 A1	22-05-1993
			DE 69230848 D1	04-05-2000
			DE 69230848 T2	07-12-2000
			EP 0543570 A2	26-05-1993
			JP 2834376 B2	09-12-1998
			JP 6069891 A	11-03-1994
DE 19848989	A	11-05-2000	DE 19848989 A1	11-05-2000
			CA 2347687 A1	04-05-2000
			WO 0025465 A1	04-05-2000
			DE 59906383 D1	28-08-2003
			EP 1123596 A1	16-08-2001